

CANBAT



HIGH RATE BATTERIES - CHR



HIGH RATE APPLICATIONS

CHR is our range of High Rate batteries, specifically designed for uninterruptible power supply (UPS) applications. High Rate batteries are available in a wide range of capacities, making them the perfect choice for UPS applications of all sizes.

Volts available: 6V and 12V

Capacities: from 2.2 Ah up to 250 Ah

Operating temperature: from -20°C to +55°C

Design life: 12 years

PERFORMANCE, DURABILITY AND SAFETY

The most important asset for many businesses is data. Whether it's customer data, employee data or financial data, no business can afford to lose it. Unfortunately, unexpected power interruptions may lead to a loss of data, which could potentially cost thousands of dollars. In order to solve this issue, Canbat has developed the highest performing High Rate batteries, especially designed for back-up power systems. Our batteries have a proven track record to be the most reliable in the industry, backed up with the best 12 months warranty in Canada.

Here is a sample selection of the batteries available in the CHR series, please visit www.canbat.ca for the full range.

Model	Voltage (V)	Capacity (Ah)	Length		Width		Height		Total Height		Weight		Terminal Type
			MM	IN	MM	IN	MM	IN	MM	IN	KG	LBS	
CHR100-6	6	100	196	7.72	170	6.69	207	8.15	213	8.39	15.60	34.39	T6
CHR150-6	6	150	260	10.24	180	7.09	247	9.72	253	9.96	21.20	46.74	T7
CHR200-6	6	200	322	12.68	178	7.01	228	8.98	234	9.21	30.50	67.24	T11
CHR2.2-12	12	2.2	178	7.01	35	1.38	60	2.36	66	2.60	0.96	2.12	T1
CHR5.4-12	12	5.4	90	3.54	70	2.76	101	3.98	107	4.21	177.00	390.22	T1
CHR6-12	12	6	151	5.94	65	2.56	93.5	3.68	99	3.90	2.18	4.81	T1
CHR6.5-12	12	6.5	151	5.94	51	2.01	93	3.66	98	3.86	1.90	4.19	T1
CHR7-12	12	7	151	5.94	65	2.56	93.5	3.68	99	3.90	2.45	5.40	T1
CHR9-12	12	9	151	5.94	65	2.56	93.5	3.68	99	3.90	2.66	5.86	T1
CHR12-12	12	12	151	5.94	98	3.86	95	3.74	101	3.98	4.20	9.26	T1
CHR18-12	12	18	182	7.17	77	3.03	168	6.61	168	6.61	6.00	13.23	T3
CHR24-12	12	24	167	6.57	175	6.89	125	4.92	125	4.92	8.80	19.40	T3
CHR27-12	12	27	165	6.50	125	4.92	172	6.77	175	6.89	7.90	17.42	T12
CHR35-12	12	35	195	7.68	130	5.12	164	6.46	180	7.09	10.50	23.15	T10
CHR38-12	12	38	197	7.76	165	6.50	170	6.69	170	6.69	13.00	28.66	T6
CHR40-12	12	40	198	7.80	166	6.54	171	6.73	171	6.73	13.20	29.10	T3
CHR55-12	12	55	229	9.02	138	5.43	200	7.87	203	7.99	17.30	38.14	T6
CHR65-12	12	65	348	13.70	167	6.57	178	7.01	178	7.01	21.00	46.30	T6
CHR75-12	12	75	259	10.20	168	6.61	208	8.19	214	8.43	22.30	49.16	T6
CHR95-12	12	95	305	12.01	168	6.61	207	8.15	210	8.27	27.40	60.41	T6
CHR100-12	12	100	330	12.99	173	6.81	212	8.35	220	8.66	30.60	67.46	T11
CHR110-12	12	110	326	12.83	170	6.69	213	8.39	216	8.50	31.40	69.23	T8
CHR120-12	12	120	410	16.14	177	6.97	225	8.86	225	8.86	37.60	82.89	T11
CHR150-12	12	150	485	19.09	170	6.69	240	9.45	240	9.45	43.50	95.90	T11
CHR155-12	12	155	335	13.19	172	6.77	275	10.83	278	10.94	42.40	93.48	T8
CHR200-12	12	200	522	20.55	240	9.45	218	8.58	224	8.82	62.50	137.79	T11

THE MOST RELIABLE BATTERY FOR UPS APPLICATIONS

In the event of a power outage, UPS systems provide back-up power to your equipment. The most important component in any UPS is the battery. Whether the UPS is hooked up to your personal computer at home, or to your equipment at work, Canbat offers top-performing batteries you can count on. If you don't have high performing batteries in your UPS during a power outage, you're putting yourself at risk of losing data. An unexpected power surge or blackout could erase hours of hard work and even damage your equipment. You can avoid all that by ensuring your UPS is equipped with a Canbat High Rate battery. Examples of equipment that utilize UPS systems include: point-of-sale terminals, desktop computers and security cameras. Installing a Canbat battery in your UPS will ensure your business continues to run, even during blackouts.

BEST WARRANTY IN CANADA

Canbat offers a hassle-free and easy replacement warranty on all its batteries. If your battery stops working within the first 12 months, we will replace it for you for free. That's a promise we won't break!

